

サイズ	サイズ大				サイズ小				Y	Z	L32MD重量(kg)
	C1(フェールル)	P1	D2(溶接)	d1	C2(フェールル)	P2	D1(溶接)	d2			
10A× 8A	34.0	27.5	17.3	14.0	34.0	27.5	13.8	10.5	30.8	30.8	0.04
15A× 8A	34.0	27.5	21.7	18.4	34.0	27.5	13.8	10.5	40.8	40.8	0.04
15A×10A	34.0	27.5	21.7	18.4	34.0	27.5	17.3	14.0	35.8	35.8	0.04
1.0S× 8A	50.5	43.5	25.4	23.0	34.0	27.5	13.8	10.5	58.0	55.0	0.10
1.0S×10A	50.5	43.5	25.4	23.0	34.0	27.5	17.3	14.0	58.0	55.0	0.11
1.0S×15A	50.5	43.5	25.4	23.0	34.0	27.5	21.7	18.4	58.0	55.0	0.11
1.5S× 8A	50.5	43.5	38.1	35.7	34.0	27.5	13.8	10.5	58.0	55.0	0.08
1.5S×10A	50.5	43.5	38.1	35.7	34.0	27.5	17.3	14.0	58.0	55.0	0.09
1.5S×15A	50.5	43.5	38.1	35.7	34.0	27.5	21.7	18.4	58.0	55.0	0.09
1.5S×1.0S	50.5	43.5	38.1	35.7	50.5	43.5	25.4	23.0	87.0	87.0	0.11
2.0S×1.0S	64.0	56.5	50.8	47.8	50.5	43.5	25.4	23.0	87.0	87.0	0.17
2.0S×1.5S	64.0	56.5	50.8	47.8	50.5	43.5	38.1	35.7	87.0	87.0	0.17
2.5S×1.0S	77.5	70.5	63.5	59.5	50.5	43.5	25.4	23.0	87.0	87.0	0.24
2.5S×1.5S	77.5	70.5	63.5	59.5	50.5	43.5	38.1	35.7	87.0	87.0	0.26
2.5S×2.0S	77.5	70.5	63.5	59.5	64.0	56.5	50.8	47.8	87.0	87.0	0.28
3.0S×1.0S	91.0	83.5	76.3	72.3	50.5	43.5	25.4	23.0	87.0	87.0	0.31
3.0S×1.5S	91.0	83.5	76.3	72.3	50.5	43.5	38.1	35.7	87.0	87.0	0.31
3.0S×2.0S	91.0	83.5	76.3	72.3	64.0	56.5	50.8	47.8	87.0	87.0	0.34
3.0S×2.5S	91.0	83.5	76.3	72.3	77.5	70.5	63.5	59.5	87.0	87.0	0.37
3.5S×2.0S	106.0	97.0	89.1	85.1	64.0	56.5	50.8	47.8	110.0	110.0	0.46
3.5S×2.5S	106.0	97.0	89.1	85.1	77.5	70.5	63.5	59.5	110.0	110.0	0.54
3.5S×3.0S	106.0	97.0	89.1	85.1	91.0	83.5	76.3	72.3	110.0	110.0	0.55
4.0S×1.5S	119.0	110.0	101.6	97.6	50.5	43.5	38.1	35.7	129.0	122.0	0.60
4.0S×2.0S	119.0	110.0	101.6	97.6	64.0	56.5	50.8	47.8	147.0	140.0	0.71
4.0S×2.5S	119.0	110.0	101.6	97.6	77.5	70.5	63.5	59.5	147.0	140.0	0.76
4.0S×3.0S	119.0	110.0	101.6	97.6	91.0	83.5	76.3	72.3	129.0	122.0	0.68
4.0S×3.5S	119.0	110.0	101.6	97.6	106.0	97.0	89.1	85.1	147.0	140.0	0.79
4.5S×4.0S	130.0	122.0	114.3	108.3	119.0	110.0	101.6	97.6	156.5	156.5	1.17
5.0S×4.0S	155.0	146.0	139.8	133.8	119.0	110.0	101.6	97.6	186.5	186.5	1.78

※概算重量としてL31MD、L31WMD、L32WMDは上記L32MDを参考にして下さい。