


# ヘルール×フランジ アダプター F-ADAPTER



単位:mm

サイズ	C	P	d	F	L	重量(kg)
ヘルール×フランジ(10k)						
10A×10A	34.0	27.5	14.0	90.0	50.0	0.57
15A×15A	34.0	27.5	18.4	95.0	50.0	0.62
1.0S×10A	50.5	43.5	23.0	90.0	50.0	0.62
1.0S×15A	50.5	43.5	23.0	95.0	50.0	0.63
1.0S×20A	50.5	43.5	23.0	100.0	50.0	0.83
1.0S×25A	50.5	43.5	23.0	125.0	50.0	1.22
1.5S×15A	50.5	43.5	35.7	95.0	50.0	0.69
1.5S×20A	50.5	43.5	35.7	100.0	50.0	0.86
1.5S×25A	50.5	43.5	35.7	125.0	50.0	1.22
1.5S×32A	50.5	43.5	35.7	135.0	50.0	1.57
1.5S×40A	50.5	43.5	35.7	140.0	50.0	1.65
2.0S×20A	64.0	56.5	47.8	100.0	50.0	0.89
2.0S×25A	64.0	56.5	47.8	125.0	50.0	1.29
2.0S×32A	64.0	56.5	47.8	135.0	50.0	1.63
2.0S×40A	64.0	56.5	47.8	140.0	50.0	1.71
2.0S×50A	64.0	56.5	47.8	155.0	50.0	2.02
2.5S×50A	77.5	70.5	59.5	155.0	50.0	2.12
2.5S×65A	77.5	70.5	59.5	175.0	50.0	2.84
3.0S×65A	91.0	83.5	72.3	175.0	50.0	2.90
3.0S×80A	91.0	83.5	72.3	185.0	50.0	2.90
4.0S×100A	119.0	110.0	97.6	210.0	60.0	3.55

※上記以外のフランジ、面間、異径サイズも製作致します。